

Amendments to the Claims:

This listing of the claims will replace all prior versions, and listings, of the claims in the application.

Listing of the Claims:

Claims 1-2 (canceled)

Claim 3 (previously presented): The system of claim 22

wherein each photocell generates a light signal and a reset signal;
wherein the sequential readout circuit determines a difference between the light signal and the reset signal for each photocell in the array in a time sequential manner.

Claim 4 (canceled)

Claim 5 (previously presented): The system of claim 22 further comprising:

an integration capacitor having a first electrode for coupling to the input of the amplifier and a second electrode for coupling to the output of the amplifier; wherein the amplifier includes a charge transfer mode and a unity gain mode.

Claim 6 (previously presented): The system of claim 22 wherein the sequential readout circuit includes

a level shifting circuit that includes a first electrode coupled to the negative input terminal of the amplifier and a second electrode coupled to the output terminal of the amplifier for performing level shifting of the output of the amplifier.

Claim 7 (previously presented): The system of claim 22 wherein the sequential readout circuit includes

a gain manipulation circuit that includes a first electrode coupled to the negative input terminal of the amplifier and a second electrode coupled to the output terminal of the amplifier for performing gain manipulation of the amplifier.

Claim 8 (previously presented): The system of claim 22 wherein each photocell includes

a photodiode for detecting light and responsive thereto for generating a voltage representation thereof; wherein the photodiode includes an integration node;

a first transistor coupled to the photodiode for resetting the integration node in response to a reset signal;

a second transistor coupled to the integration node for shifting the level of the voltage at the integration node; and

a third transistor coupled to the second transistor for reading out the level-shifted voltage in response to a read signal.

Claims 9-10 (canceled)

Claim 11 (previously presented): The sequential readout circuit of claim 23 wherein the amplifier determines the difference between the light signal and the reset signal for the photocells in the array in a time sequential manner.

Claims 12-13 (canceled)

Claim 14 (previously presented): The sequential readout circuit of claim 23 wherein the amplifier includes a charge transfer mode, a unity gain mode, a first input; and an output; and wherein the circuit further includes an integration capacitor having a first electrode for coupling to the negative input terminal and a second electrode for coupling to the output terminal of the amplifier.

Claim 15 (previously presented): The sequential readout circuit of claim 23 further comprising:
a level-shifting mechanism that includes a first electrode coupled to the negative input terminal of the amplifier and a second electrode coupled to the output terminal of the amplifier for performing level shifting of the output of the amplifier.

Claim 16 (previously presented): The sequential readout circuit of claim 23 further comprising:
a gain mechanism that includes a first electrode coupled to the negative input terminal of the amplifier and a second electrode coupled to the output terminal of the amplifier for performing gain manipulation of the amplifier.

Claim 17 (previously presented): The sequential readout circuit of claim 23 wherein each photocell includes
a photodiode for detecting light and responsive thereto for generating a voltage representation thereof; wherein the photodiode includes an integration node;
a first transistor coupled to the photodiode for resetting the integration node in response to a reset signal;

a second transistor coupled to the integration node for shifting the level of the voltage at the integration node; and
a third transistor coupled to the second transistor for reading out the level-shifted voltage in response to a read signal.

Claims 18-21 (canceled)

Claim 22 (currently amended): A system comprising:

- a) an array of photocells that are arranged in rows and columns; and
- b) a sequential readout circuit for sequentially reading out the value of the photocells one photocell at a time; wherein the sequential readout circuit includes

~~for each column~~

~~a sampling capacitor that includes a first electrode for coupling to a respective column and a second electrode; and
a switch that includes a first electrode coupled to the second electrode of the sampling capacitor, a second electrode, and a third electrode for receiving a sample control signal; wherein the switch selectively couples the first electrode of the switch to the second electrode of the switch when the sample control signal is asserted;~~

a first sampling circuit that includes a first electrode for coupling to a first column and a second electrode;

a first switch that includes a first electrode coupled to the second electrode of the first sampling circuit, a second electrode, and a third electrode for receiving a first sample control signal; wherein the first switch selectively couples the first electrode of the first switch to the second electrode of the first switch when the first sample control

signal is asserted; wherein the first sampling circuit samples a light signal and a reset signal from each photocell in the first column;

a second sampling circuit that includes a first electrode for coupling to a second column and a second electrode;

a second switch that includes a first electrode coupled to the second electrode of the second sampling circuit, a second electrode, and a third electrode for receiving a second sample control signal; wherein the second switch selectively couples the first electrode of the second switch to the second electrode of the second switch when the second sample control signal is asserted; wherein the second sampling circuit samples a light signal and a reset signal from each photocell in the second column; and

an amplifier that includes a negative input terminal coupled to the second electrode of the first switch and the second electrode of the first switch; wherein the amplifier includes an output terminal for generating a signal that corresponds to the amount of light received by a particular photocell in the array.

Claim 23 (currently amended): A sequential readout circuit for coupling to an array of photocells that includes a plurality of photocells that are arranged in rows and columns, each photocell generating a light signal during a first period of time that represents received light and a reset signal after being reset, the sequential readout circuit comprising:

~~for each column~~

~~a) a sampling capacitor that includes a first electrode for coupling to a respective column and a second electrode;~~

~~b) a switch that includes a first electrode coupled to the second electrode of the sampling capacitor, a second electrode, and a third~~

~~electrode for receiving a sample control signal; wherein the switch selectively couples the first electrode of the switch to the second electrode of the switch when the sample control signal is asserted; and~~

e)

a first sampling circuit that includes a first electrode for coupling to a first column and a second electrode;

a first switch that includes a first electrode coupled to the second electrode of the first sampling circuit, a second electrode, and a third electrode for receiving a first sample control signal; wherein the first switch selectively couples the first electrode of the first switch to the second electrode of the first switch when the first sample control signal is asserted; wherein the first sampling circuit samples a light signal and a reset signal from each photocell in the first column;

a second sampling circuit that includes a first electrode for coupling to a second column and a second electrode;

a second switch that includes a first electrode coupled to the second electrode of the second sampling circuit, a second electrode, and a third electrode for receiving a second sample control signal; wherein the second switch selectively couples the first electrode of the second switch to the second electrode of the second switch when the second sample control signal is asserted; wherein the second sampling circuit samples a light signal and a reset signal from each photocell in the second column;

an amplifier that includes a negative input terminal coupled to the second electrode of the first switch and second electrode of the second switch; wherein the amplifier includes an output terminal for generating a signal that corresponds to the amount of light received by a particular photocell in the array.

Claim 24 (previously presented): The sequential readout circuit of claim 23 wherein the sequential readout circuit sequentially reads out a value of the photocells one photocell at a time

Claim 25 (previously presented): The system of claim 22 wherein the sequential readout circuit measures a light signal from a photocell, measures a reset signal from a photocell, and stores a charge that represents the difference between the light signal and the reset signal.

Claim 26 (previously presented): The sequential readout circuit of claim 23 wherein the sequential readout circuit measures the light signal from a photocell, measures the reset signal from a photocell, and stores a charge that represents the difference between the light signal and the reset signal.

Claim 27 (new): The system of claim 22 wherein the first sampling circuit includes a sampling capacitor.

Claim 28 (new): The system of claim 22 wherein the second sampling circuit includes a sampling capacitor.

Claim 29 (new): The sequential readout circuit of claim 23 wherein the first sampling circuit includes a sampling capacitor.

Claim 30 (new): The sequential readout circuit of claim 23 wherein the second sampling circuit includes a sampling capacitor.

Claim 31 (new): A method for reading out values of an array of photocells that are arranged in rows and columns comprising:

sampling the light signal of all the photocells in a first row by utilizing a sampling circuit that corresponds to a particular column of the array;
holding the light signal;
after the photocells of the first row have been reset, sampling the reset signals of photocells of the first row by using the sampling circuit;
determining a difference between the light signal and the reset signal of a first photocell in the first row by utilizing a charge conversion circuit that is coupled to the sampling circuit; and
sequentially reading out the values of the array of photocells.

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.